

Growatt ShineLink-X

- Cable free, easy installation
- Dynamic IP, plug and play
- Communication distance up to 120m
- Support up to 8 devices
- Built-in memory for up to one month of data
- Online monitoring and maintenance



P O W E R
- I N G O
T O M O -
R R O W O

GROWATT

www.ginverter.com

Datasheet	ShineLink-X
Communication Interface	
RF433	Yes
RF433(No barrier wall)	Up to 120 m
RF433(two walls blocking)	20 m
Power Supply	
Power consumption	<2W standby, <5W peak
Voltage range	196V~250V
Frequency	50/60Hz
General Specifications	
Dimensions(L/W/H)	105/85/26mm
Weight	< 1kg
Mounting options	Tabletop/wall-mount
Protection degree	IP30
Display	LED
Ambient temperature range	-20 to 65 °C
Humidity	0-95% (non condensing)
Features	
Remote firmware upgrade	Yes
Max. number of devices to monitor	8(RF433)
Warranty	1 years
CE	